

Assembly Instructions for the Mounting Stand Kit and ECE 5000

1. Unpack your mounting stand kit (Figure 1). The kit includes a mounting stand post, base, and four screws.
2. Assemble the mounting stand post to the base using the four screws. A 1/8" hex wrench should be used to install the screws.

Note: The post is offset to the left (Figure 2).



Figure 1. Mounting Stand Kit



Figure 2. Post Installed on Base

3. Remove the reflector's filler plate by removing the four screws that hold it in place (Figure 3). Place the glass UV shield on the reflector and reinstall the filler plate with the four screws (Figure 4).

Important: There is a pocket on the underside of the retainer bracket. Ensure that the glass shield is sitting in the pocket. If the glass shield is not positioned correctly, there is the potential to crack the glass.




Figure 3. Reflector with Filler Plate Removed



Figure 4. Glass Shield Installed

4. Locate the reflector mounting brackets and mounting screws.
5. Install the brackets to the rear of the reflector. Install the two bypass connectors into J4 (PN 41069) and J5 (PN 41068) appropriately (Figure 6).




Figure 5. Reflector Mounting Bracket



Figure 6. Bypass Connectors Installed

6. Place the reflector assembly on the mounting stand. Install the fireproof work surface on the stand.
7. Position the urethane UV shield in front of the reflector.



Figure 7. Attach Reflector to Mounting Stand




Figure 8. Position UV Shield to Mounting Stand

8. Attach the connector cable between the power supply and the back of the reflector.
9. Your mounting stand kit is assembled and ready for use.



Figure 9. Connect Power Supply to Reflector

**For detailed operating instructions,
please refer to the ECE Flood Lamp
User Guide.**



Figure 10. Complete Assembly, Front

DYMAX EDGE™
LISTEN. ENVISION. DELIVER.

In addition to our light-curing equipment, Dymax also offers high-performance adhesives designed to rapidly bond glass, metal, and plastic substrates upon exposure to UV/Visible light and a variety of dispensing equipment. Our products are perfectly matched to work seamlessly with each other, providing design engineers with tools to dramatically improve manufacturing efficiency and reduce costs. Dymax is committed to providing the best chemistry, curing equipment, and dispensing systems that offer customers complete manufacturing solutions for their challenging applications.



© 2013 Dymax Corporation. All rights reserved. All trademarks in this bulletin, except where noted, are the property of, or used under license by Dymax Corporation, U.S.A.

The data contained in this bulletin is of a general nature and is based on laboratory test conditions. Dymax Europe GmbH does not warrant the data contained in this bulletin. Any warranty applicable to products, its application and use is strictly limited to that contained in Dymax Europe GmbH's General Terms and Conditions of Sale published on our homepage http://www.dymax.com/de/pdf/dymax_europe_general_terms_and_conditions_of_sale.pdf. Dymax Europe GmbH does not assume any responsibility for test or performance results obtained by users. It is the user's responsibility to determine the suitability for the product application and purposes and the suitability for use in the user's intended manufacturing apparatus and methods. The user should adopt such precautions and use guidelines as may be reasonably advisable or necessary for the protection of property and persons. Nothing in this bulletin shall act as a representation that the product use or application will not infringe a patent owned by someone other than Dymax Corporation or act as a grant of license under any Dymax Corporation Patent. Dymax Europe GmbH recommends that each user adequately test its proposed use and application of the products before actual repetitive use, using the data contained in this bulletin as a general guide. QS057EU 3/21/2013

Dymax Corporation
860.482.1010
info@dymax.com
www.dymax.com

Dymax Oligomers & Coatings
860.626.7006
oligomers&coatings@dymax.com
www.dymax-oc.com

Dymax Europe GmbH
+49 (0) 611.962.7900
info_de@dymax.com
www.dymax.de

Dymax UV Adhesives & Equipment (Shenzhen) Co Ltd
+86.755.83485759
dymaxasia@dymax.com
www.dymax.com.cn

Dymax UV Adhesives & Equipment (Shanghai) Co Ltd
+86.21.37285759
dymaxasia@dymax.com
www.dymax.com.cn

Dymax Asia (H.K.) Limited
+852.2460.7038
dymaxasia@dymax.com
www.dymax.com.cn

Dymax Korea LLC
82.2.784.3434
info@dymax.kr
www.dymax.co.kr